

Magnum 6K16 Configuration Guide



GarrettCom™
Industrial Networking at Its Best™

Magnum 6K16 Managed Switch, base unit with front-to-rear fan cooling, for rack mounting or table-top. May be configured with a variety of 10/100/1000 Mb fiber and copper port connector types via selection from a family of port modules. 16 ports max. Two 6K16 units can be mounted side by side in a 19" rack. Wire speed filtering and forwarding across all ports, 2 alarm contacts, 802.3x flow control, 802.1p priority packet processing, 4K node address table, 240KB packet buffers.

Note: MNS-6K software license is included with Base Unit.

Step 1. Choose 6K16 chassis and power input type:

Model #	Base Unit, Description
6K16	AC Power
6K16-24 VDC	24V (18-36) DC power
6K16-48 VDC	-48V (36-70) DC power
6K16-125 VDC	125V (88-300) DC power



Step 2. Choose 1 module for slot A and/or B (may be blank):

Note: If PoE module is desired, see [PoE Configuration Guide](#).

Module Model #	10/100	10BASE-FL	100BASE-FX(MM)	100BASE-FX(SM)	Gigabit
6KP8-RJ45	8				
6KP8-45-2MT	6		2 (MTRJ)		
6KP8-45-2SLC	6			2 (15km LC)	
6KP6-RJ10ST	4	2 (ST)			
6KP6-RJMST	4		2 (ST)		
6KP6-RJMST	4		2 (SC)		
6KP6-RJSSC	4			2 (20km SC)	
6KP6-RJSSCL	4			2 (40km SC)	
6KP8-45MT	4		4 (MTRJ)		
6KP8-45MLC	4		4 (LC)		
6KP8-45SLC	4			4 (15km LC)	
6KP4-F10ST		4 (ST)			
6KP4-FLSTFX		2 (ST)	2 (ST)		
6KP4-FXST			4 (ST)		
6KP4-FXSC			4 (SC)		
6KP6-MT10ST		2 (ST)	4 (MTRJ)		
6KP8-MTRJ			8 (MTRJ)		
6KP8-MLC			8 (LC)		
6KP8-SLC				8 (15km LC)	

Gigabit Modules using GBICs (see Step 3)

6KP5-G4RJ	4				1 GBIC
6KP3-G2SC			2 (SC)		1 GBIC
GBPM-COTX					1 GBIC
GBPM-2OTX					2 GBIC

Gigabit Modules, fixed ports

6KP2-2GSX					2 SX
6KP2-2GCU					2 CU
6KP5-1CU4MT			4 (MTRJ)		1 CU
6KP3-1CU2FXT			2 (ST)		1 CU
6KP5-1CU4RJ	4				1 CU

Gigabit Modules, fixed ports—Using Small form factor (SFP) transceivers

6KP2-2GSFP					2 SFP
6KP2-1GCU1SFP					1SFP, 1CU
6KP1-1GSFP					1 SFP
6KP1-1GCU					1 CU

Step 3 (Opt) Choose GBICs or SFPs for Gig Ports (if configured) in Slot A and/or B:

Model #	Description (Ports for GBPM-COTX / 6KP5-G4RJ / 6KP3-G2SC)
GBIC-SXSC	One 1000BASE-SX port with m.m. SC fiber connector
GBIC-LXSC10	One 1000BASE-LX/LH port 1310nm s.m. SC 10Km
GBIC-LXSC25	One 1000BASE-LX/LH port 1310nm s.m. SC 25Km
GBIC-TP	One IEEE 802.3ab TP port, RJ-45 connector
GBIC-ZXSC40	One 1000BASE-ZX port 1550nm s.m. SC 40Km
GBIC-ZXSC70	One 1000BASE-ZX port 1550nm s.m. SC 70Km
GBIC-ZXSC120	One 1000BASE-ZX port 1550nm s.m. SC 120Km

Gb SFP fiber optic transceivers

SFP-SX	Gb SX, 850nm wavelength, 500 meters distance
SFP-LX10	Gb LX, 1310nm wavelength, 10km distance
SFP-LX25	Gb LX, 1310nm wavelength, 25km distance
SFP-ZX40	Gb ZX, 1550nm wavelength, 40km distance
SFP-ZX70	Gb ZX, 1550nm wavelength, 70km distance

Step 4. Choose options & extras:

Model #	Description
6KM-BLNK	Blank cover for 1 unused (A) module slot
CONSOLE CBL	Console attachment cable serial null Modem (aka X-modem) cable with DB9 connectors
CONSOLE USB	As above, but with a USB connector
DUAL-SRC	Two separate power inputs (24/ 48/ or 125V)
S-Ring Key	Software, self-healing ring, includes RS-Ring
K16-2TRAY	Rack-mount Tray holds 2 6K16s side-by-side
K16-RMB	Two metal Brackets for 19" Rack Mount
K16-RMB-CTR	2 Metal Brackets for center-mount in 19" Rack
K16-EXTN-KIT	Convert K16-RMB/K16-2TRAY to ETSI or 23"
CONFORM14 CR	Conformal coating 14 mil – request quote
ALARM TRMBLK	2 Alarm contacts, incl., std feature on 6K16